

Users and Passwords

AGRICULTURE

February 2019

TRIMBLE RESELLER CONFIDENTIAL

Managing Users and Passwords

This document provides the instructions for management and maintenance of users and passwords for the Trimble® Precision-IQ™ application. When enabled, Precision-IQ allows for multiple user/operators to login and perform a variety of tasks, as needed.

Contents			
Add or Edit a User/Operator	Enable User/Operator Login	Delete a User/Operator Profile	Restore Default Preferences

Add or Edit a User/Operator

Follow the steps below to add or edit a user/operator for the Precision-IQ application:

1. From the Home screen of Precision-IQ, tap **Settings**. Then, on the Settings screen, tap **Operators and Passwords**.
2. In the Operators section, tap the option to **Enable Operators**:



Note: By default, the **Enable Operators** option is not selected.

3. Select an action:
 - a. **Add User:** In the Users section, tap **Add User**.
 - b. **Edit User:** In the Users section, tap the user that you want to edit.
4. A pop-up will appear for you to add a **New User Profile:** or edit **User Settings**.
5. Enter the following information:
 - a. **Operator ID:** Create or modify a unique user name for the operator.
 - b. **Password:** Enter a unique password or change an existing password.

<http://agpartners.trimble.com>

www.trimble.com

© 2018, Trimble Inc. All rights reserved. Trimble, the Globe & Triangle logo are trademarks of Trimble Trimble Inc., registered in the United States and in other countries. Precision-IQ is a trademark/trademarks of Trimble Inc. All other trademarks are the property of their respective owners.

- c. Confirm Password: Re-enter the password. Passwords must match.
- d. Picture (*optional*): Tap the silhouette to activate the forward camera of the display.

You can take a photo of the operator to associate with the profile. Tap **Capture** to take the picture, then tap **Done** to save it to the profile.

6. Tap **Create User** or **Save Changes**.

Enable User/Operator Login

Follow the steps below to enable Precision-IQ login option and for instructions to login to the application:

1. From the Home screen of Precision-IQ, tap **Settings**. Then, on the Settings screen, tap **Operators and Passwords**.
2. In the Operators section, tap the option to **Enable Operators**, if it's not already selected:



Note: By default, the **Enable Operators** option is *not* selected.

(*Optional*) In the Persistent User section, tap the **Persistent Login** option to set a user/operator to login by default:



Note: By default, the Persistent Login option is not selected.

3. Exit the Precision-IQ application.
4. To login to Precision-IQ, tap the **Precision-IQ** icon on the Launcher screen. Instead of the Home screen, a login window appears.
5. Enter the password/PIN and tap **Log In**.

Delete a User/Operator Profile

Follow the steps below to delete a user/operator profile:

1. From the Home screen of Precision-IQ, tap **Settings**. Then, on the Settings screen, tap **Operators and Passwords**.
2. In the Operators section, tap the option to **Enable Operators**, if it's not already selected.
3. In the Users section, tap the user that you want to delete. A pop-up will appear for you to edit the **User Settings**.
4. Tap **Delete User**. The user profile is deleted immediately.

Restore Default Preferences

As part of the day-to-day operation of Precision-IQ, a user/operator has a variety of preferences that can be set. Over time, you may wish to reset preferences for a user or for the entire device. Follow the steps below to restore default preferences:

1. From the Home screen of Precision-IQ, tap **Settings**. Then, on the Settings screen, tap **Operators and Passwords**.
2. In the Restore Default section, tap one of the following options:
 - **Restore Default User Preferences:** Tap this option to restore the preferences of the currently logged in user.
 - **Restore Preferences to Factory Defaults:** Tap this option to restore the display to its factory default settings.
3. A confirmation pop-up will display. Tap **Restore Default Preferences** to continue or tap **Cancel** to cancel the restore operation.

For More Information

Contact your local Trimble Regional Sales Manager.